



SPARTAN GoCam 3G (GC-EUxb) Remote Controlling your camera trap using SMS:

(PLEASE NOTE: SOME CELLULAR TOWERS DO NOT SUPPORT ALL COMMANDS. If the unit sends you a text response of "Network Busy" this means the tower/service area does not support the command. This is not a manufacturer/camera issue).

The Spartan® GoCam 3G camera can be controlled by sending SMS commands to the camera's SIM card phone number.

The Commander Phone Number

The Recipient Phone numbers that you set in the setup process for "Phone1" / "Phone2" / "Phone3" & "Phone4" will be the commander phone numbers i.e. the ones that can control the camera via SMS.

SMS Switch

In order to use the SMS control function, the user needs to set the switch to **ON** in the setup process.

Spartan® GoCam 3G SMS Command Code List

COMMAND	TEXT MESSAGE	SMS RESPONSE YOU WILL GET
Take Photo and Send Now	*500#	Picture sending ("Invalid" when the camera mode is Video.)
Signal Level	*150#	The signal is very weak/weak/good/very good
Power Level	*201#	Battery Level 1 to 5 (low to high)
Send Via MMS	*120#0#	Send via MMS
Send Via Internet	*120#1#	Send via Internet (When send via is Internet, "Send To" will be modified to Email only)
Send To Phone	*130#0#	Send to phone
Send To Email	*130#1#	Send to email
Send To Both	*130#2#	Send to both (When send via is Internet, "Send To" will be modified to Email only)
Add Phone	*100# <i>number</i> #	Phone number added (<i>number</i> = the relevant cell phone number you want to add)
Delete Phone	*101# <i>number</i> #	Phone number deleted (<i>number</i> = the relevant cell phone number you want to delete)
Add Email	*110# <i>email</i> #	Email added (<i>email</i> = the relevant email address you want to add)
Delete Email	*111# <i>email</i> #	Email deleted (<i>email</i> = the relevant email address you want to delete)
Camera Mode Photo	*200#0#	Set to photo mode
Camera Mode Video	*200#1#	Set to video mode
Send Mode Instant	*140#0#	Send instant photo
Send Mode Daily Report	*140#1#	Send daily report
Send Mode Off	*140#2#	Send is off
Set PIR Level to High	*202#0#	PIR sensitivity high
Set PIR Level to Normal	*202#1#	PIR sensitivity normal
Set PIR Level to Low	*202#2#	PIR sensitivity low
Set PIR Level to Off	*202#3#	PIR sensitivity off
Turn SMS Off	*104#	Camera Turned Off

Please let me know if you have any questions or require any assistance with the setup.

Kind regards,

Chris & Nicola Pearson | CAMERA TRAPS cc | chris@cameratrap.co.za | nicola@cameratrap.co.za

Cell +27 83 560 0555 | +27 82 422 0356 | F +27 86 505 5536

South Africa

www.CameraTraps.co.za