



**SPARTAN GoCam 4G – Remote Controlling your camera trap using SMS:**

*(PLEASE NOTE: SOME CELLULAR TOWERS DO NOT SUPPORT ALL COMMANDS. If the unit sends you a text response of “Network Busy” this means the tower/service area does not support the command. This is not a manufacturer/camera issue).*

**The Spartan® GoCam 4G camera can be controlled by sending SMS commands to the camera’s SIM card phone number.**

**The Commander Phone Number** - The Recipient **Phone1** will be the commander phone numbers i.e. the one that can control the camera via SMS commands.

**Power Saving** - In order to use the SMS remote control function, the user needs to set the switch to **OFF** in the setup process.

**Status Response (SMS)** - In order to use the SMS control function, the user needs to tick this box in the setup process

If checked, the camera will send The Commander Phone Number (Phone1) a return SMS confirming the command - whether sending via MMS or Email (User must have a valid cell phone number input for Phone1 for this function to operate).

*Spartan® GoCam 4G SMS Command Code List*

COMMAND	TEXT MESSAGE	SMS RESPONSE YOU WILL GET
Take Photo and Send Now	*500#	Picture sending ("Invalid" when the camera mode is Video.)
Signal Level	*150#	The signal is very weak/weak/good/very good
Power Level	*201#	Battery Level 1 to 5 (low to high / Full)
Send Via MMS	*120#0#	Send via MMS
Send Via Internet	*120#1#	Send via Internet (When send via is Internet, "Send To" will be modified to Email only)
Send To Phone	*130#0#	Send to phone
Send To Email	*130#1#	Send to email
Send To Both	*130#2#	Send to both (When send via is Internet, "Send To" will be modified to Email only)
Add Phone	*100# <i>number</i> #	Phone number added ( <i>number</i> = the relevant cell phone number you want to add)
Delete Phone	*101# <i>number</i> #	Phone number deleted ( <i>number</i> = the relevant cell phone number you want to delete)
Add Email	*110# <i>email</i> #	Email added ( <i>email</i> = the relevant email address you want to add)
Delete Email	*111# <i>email</i> #	Email deleted ( <i>email</i> = the relevant email address you want to delete)
Camera Mode Photo	*200#0#	Set to photo mode
Camera Mode Video	*200#1#	Set to video mode
Camera Mode Photo+Video	*200#2#	Set to photo+video mode
Send Mode Instant	*140#0#	Send instant photo
Send Mode Daily Report	*140#1#	Send daily report
Send Mode Off	*140#2#	Send is off
Daily Max Number	*180# <i>number</i> #	Max number reset to <i>number</i> (Number 0 = unlimited and max is 9999)
Set PIR Level to High	*202#0#	PIR sensitivity high
Set PIR Level to Normal	*202#1#	PIR sensitivity normal
Set PIR Level to Low	*202#2#	PIR sensitivity low
Set PIR Level to Off	*202#3#	PIR sensitivity off

Please let me know if you have any questions or require any assistance with the setup.

Kind regards,

Chris & Nicola Pearson | CAMERA TRAPS cc | [chris@cameratrap.co.za](mailto:chris@cameratrap.co.za) | [nicola@cameratrap.co.za](mailto:nicola@cameratrap.co.za)

Cell +27 83 560 0555 | +27 82 422 0356 | F +27 86 505 5536

South Africa

[www.CameraTraps.co.za](http://www.CameraTraps.co.za)